# acer



## *Aspire* C22 / C24 / C27

■■ **Windows 11**

intel **CORE** i5

intel **CORE** i3

Narrow Bezel

-5°-25°

**Wi-Fi 6E**
Wireless
Connection

SSD
Data Access

BlueLightShield™

Flickerless

Wide Viewing Angle

| Product views | 1. Microphones | 6. USB Type-C port | 11. Ethernet (RJ-45) port |
|---|---|---|---|
| | 2. Webcam and Webcam shutter | 7. USB 3.2 Gen 2 port | 12. Kensington lock slot |
| | 3. LCD display | 8. Two USB 3.2 Gen 1 ports | 13. Power connector (DC-in) |
| | 4. Power LED | 9. Audio combo jack | 14. USB 2.0 port |
| | 5. Power button | 10. HDMI®-out port | |

| Operating system[1, 2] | **Windows 11 Pro 64-bit.** (Acer recommends Windows 11 Pro for business.) <br> **Windows 11 Home 64-bit** <br> **UEFI Shell** |
|---|---|
| CPU and chipset[1] | **13th Gen Intel® Core™ i5-1335U** processor, Intel® Iris® X<sup>e</sup> Graphics <br> **13th Gen Intel® Core™ i3-1315U** processor, Intel® Iris® X<sup>e</sup> Graphics |
| Memory[1, 3, 4] | 32 GB / 16 GB / 8 GB / 4 GB DDR4 3200 MHz soDIMM <br> 16 GB / 8 GB / 4 GB DDR4 2666 MHz soDIMM <br> • Up to 32 GB of DDR4 3200 MHz |

| Storage[1, 5] | **Hard disk drive:** <br> • 500 GB 2.5-inch 5400 RPM | **Solid state drive:** <br> • 1024 GB / 512 GB M.2 2280 PCI-E Gen 4 SSD <br> • 1024 GB M.2 2280 PCI-E SSD <br> • 256 GB M.2 2280 PCI-E Gen 4 SSD (C22-1800 only) |
|---|---|---|

| Display | **C22-1800:** <br> Touch support: Non-touch <br> Size (inches): 20", 21.5" <br> Display max resolution: 1920 x 1080 <br> Backlight: LED <br> Brightness (cd/m2): 250nits <br> Aspect ratio: 16:9 | **C24-1800:** <br> Touch support: Non-touch <br> Size (inches): 23.8" <br> Display max resolution: 1920 x 1080 <br> Backlight: LED <br> Brightness (cd/m2): 250nits <br> Aspect ratio: 16:9 | **C27-1800:** <br> Touch support: Non-touch <br> Size (inches): 27" <br> Display max resolution: 1920 x 1080 <br> Backlight: LED <br> Brightness (cd/m2): 250nits <br> Aspect ratio: 16:9 |
|---|---|---|---|

| Audio | Built-in stereo speakers <br> DTS® Audio |
|---|---|
| Webcam | **Video conferencing:** <br> • Integrated 5.0 MP HD webcam with 2 stereo microphones |

| Communication | **WLAN:** <br> 802.11ax/ac/a/b/g/n, Wi-Fi 6E and Bluetooth® 5.0 <br> 802.11ax/ac/a/b/g/n, Wi-Fi 6 and Bluetooth® 5.0 <br> 802.11ac/a/b/g/n wireless LAN and Bluetooth® 5.0 | **LAN:** <br> Gigabit Ethernet |
|---|---|---|

| Expansion slot(s) | M.2 slot (for SSD): 1 <br> M.2 slot (for WLAN): 1 |
|---|---|

| Windows Desktop Apps[6] | **In-House:** <br> • Acer Care Center <br> • Acer Configuration Manager <br> • Acer Product Registration | • Acer User Experience Program Framework <br> • Quick Access |
|---|---|---|

| Dimensions | **C22-1800:** <br> 493.5 (W) x 37.3 (D) x 376.79 (H) mm (19.43 x 1.47 x 14.83 inches) <br> **C24-1800:** <br> 540.4 (W) x 37.3 (D) x 405.24 (H) mm (21.28 x 1.47 x 15.95 inches) <br> **C27-1800:** <br> 612.5 (W) x 37.3 (D) x 445.52 (H) mm (24.11 x 1.47 x 17.54 inches) |
|---|---|
| Hinge | Panel Tiltable from -5° to 25° |
| Power supply and adapter | 3-pin 65 W AC adapter |
| System compliance | RoHS, GS |
| Options and accessories | Cable management <br> Wireless (2.4 GHz RF) keyboard and mouse <br> USB keyboard and mouse <br> VESA mount kit (100mm*100mm) (optional) |
| Certification | BSMI, CE, FCC, CB |

1. Specifications vary depending on model.
2. 64-bit software is required to enjoy the advantages of 64-bit processing.
3. A 64-bit operating system is required to enjoy the ultimate performance of 4 GB or higher memory.
4. Memory speed may vary, depending on the CPU, chipset or memory fitted.
5. 1 GB is 1 billion bytes, 1 TB is 1000 GB. Actual formatted capacity is less and may vary depending on preloaded materials and operating environment. Recovery Management uses a portion of the stated hard disk capacity as dedicated backup space.
6. Bundled software may vary depending on hardware configuration, OS and regional availability.

**About Acer**