

CPU Support List

* Some of AMD CPU does not have integrated graphics processor. When this kind of CPU is installed, a discrete VGA card is required.

Socket (Цокъл)	Family (Фамилия)	Model (Модел)	Power (Енергия)	Core (Ядро)	Frequency (Честота)	Cache (Кеш)	CPU Rev. (Ревизия на процесор)	Since BIOS (От BIOS)
AM4*	Ryzen 9	5950X (100-000000059-00)	105W	Vermeer	3.4GHz	8MB		P4.60
AM4*	Ryzen 9	5900X (100-000000061-00)	105W	Vermeer	3.7GHz	6MB		P4.60
AM4*	Ryzen 7	5800X (100-000000063-00)	105W	Vermeer	3.8GHz	4MB		P4.60
AM4*	Ryzen 5	5600X (100-000000065-00)	65W	Vermeer	3.7GHz	3MB		P4.60
AM4	Ryzen 7	PRO 4750G(100-000000145)	65W	Renoir	3.6GHz	4MB	A1	P4.80
AM4	Ryzen 7	PRO 4750GE(100-000000152)	35W	Renoir	3.1GHz		A1	P4.80
AM4	Ryzen 5	PRO 4650G(100-000000143)	65W	Renoir	3.7GHz	3MB	A1	P4.80
AM4	Ryzen 5	PRO 4650GE(100-000000153)	35W	Renoir	3.3GHz		A1	P4.80
AM4	Ryzen 3	PRO 4350G(100-000000148)	65W	Renoir	3.8GHz	2MB	A1	P4.80
AM4	Ryzen 3	PRO 4350GE(100-000000154)	35W	Renoir	3.5GHz		A1	P4.80
AM4*	Ryzen 9	3950X (100-000000051)	105W	Matisse	3.5GHz	8MB	B0	P3.60
AM4*	Ryzen 9	3900XT(100-000000277)	105W	Matisse 2	4.1GHz			P4.20
AM4*	Ryzen 9	3900X (100-000000023)	105W	Matisse	3.8GHz	6MB	B0	P3.30
AM4*	Ryzen 9	3900 (100-000000070)	65W	Matisse	3.1GHz	6MB	B0	P3.60
AM4*	Ryzen 7	3800XT(100-000000279)	105W	Matisse 2	4.2GHz			P4.20
AM4*	Ryzen 7	3800X (100-000000025)	105W	Matisse	3.9GHz	4MB	B0	P3.30
AM4*	Ryzen 7	PRO 3700 (100-000000073)	65W	Matisse	3.6GHz	4MB	B0	P3.60
AM4*	Ryzen 7	3700X (100-000000071)	65W	Matisse	3.6GHz	4MB	B0	P3.30
AM4*	Ryzen 7	PRO 2700X (YD27BXBAM88AF)	95W	Pinnacle Ridge	3.6GHz	4MB	B2	All
AM4*	Ryzen 7	PRO 2700 (YD270BBBM88AF)	65W	Pinnacle Ridge	3.2GHz	4MB	B2	All
AM4*	Ryzen 7	2700X (YD270XBGM88AF)	105W	Pinnacle Ridge	3.7GHz	4MB	B2	All
AM4*	Ryzen 7	2700 (YD2700BBM88AF)	65W	Pinnacle Ridge	3.2GHz	4MB	B2	All
AM4*	Ryzen 7	2700E (YD270EBHM88AF)	45W	Pinnacle Ridge	2.8GHz	4MB	B2	All
AM4*	Ryzen 7	1800X (YD180XBCM88AE)	95W	Summit Ridge	3.6GHz	4MB	B1	All
AM4*	Ryzen 7	PRO 1700X (YD17XBBAM88AE)	95W	Summit Ridge	3.4GHz	4MB	B1	All
AM4*	Ryzen 7	PRO 1700 (YD170BBBM88AE)	65W	Summit Ridge	3.0GHz	4MB	B1	All
AM4*	Ryzen 7	1700X (YD170XBCM88AE)	95W	Summit Ridge	3.4GHz	4MB	B1	All

AM4*	Ryzen 7	1700 (YD1700BBM88AE)	65W	Summit Ridge	3.0GHz	4MB	B1	All
AM4*	Ryzen 5	PRO 3600 (100-000000029)	65W	Matisse	3.6GHz	3MB	B0	P3.30
AM4*	Ryzen 5	3600XT(100-000000281)	95W	Matisse 2	4.0GHz			P4.20
AM4*	Ryzen 5	3600X (100-000000022)	95W	Matisse	3.8GHz	3MB	B0	P3.30
AM4*	Ryzen 5	3600 (100-000000031)	65W	Matisse	3.6GHz	3MB	B0	P3.30
AM4*	Ryzen 5	3500X (100-000000158)	65W	Matisse	3.6GHz	3MB	B0	P3.60
AM4*	Ryzen 5	3500 (100-000000050)	65W	Matisse	3.6GHz	3MB	B0	P3.60
AM4	Ryzen 5	PRO 3400G (YD340BC5M4MFH)	65W	Picasso	3.7GHz	2MB	B1	P3.30
AM4	Ryzen 5	PRO 3400GE (YD340BC6M4MFH)	35W	Picasso	3.3GHz	2MB	B1	P3.30
AM4	Ryzen 5	3400G (YD340GC5M4MFH)	65W	Picasso	3.7GHz	2MB	B1	P3.60
AM4	Ryzen 5	3400G (YD3400C5M4MFH)	65W	Picasso	3.7GHz	2MB	B1	P3.30
AM4	Ryzen 5	3400GE (YD3400C6M4MFH)	35W	Picasso	3.3GHz	2MB	B1	P3.30
AM4*	Ryzen 5	PRO 2600 (YD260BBM6IAF)	65W	Pinnacle Ridge	3.4GHz	3MB	B2	All
AM4*	Ryzen 5	2600X (YD260XBCM6IAF)	95W	Pinnacle Ridge	3.6GHz	3MB	B2	All
AM4*	Ryzen 5	2600 (YD2600BBM6IAF)	65W	Pinnacle Ridge	3.4GHz	3MB	B2	All
AM4*	Ryzen 5	2600E (YD260EBHM6IAF)	45W	Pinnacle Ridge	3.1GHz	3MB	B2	All
AM4*	Ryzen 5	2500X (YD250XBBM4KAF)	65W	Pinnacle Ridge	3.6GHz	2MB	B2	All
AM4	Ryzen 5	PRO 2400G (YD240BC5M4MFB)	65W	Raven Ridge	3.6GHz	2MB	B0	All
AM4	Ryzen 5	PRO 2400GE (YD240BC6M4MFB)	35W	Raven Ridge	3.2GHz	2MB	B0	All
AM4	Ryzen 5	2400G (YD2400C5M4MFB)	65W	Raven Ridge	3.6GHz	2MB	B0	All
AM4	Ryzen 5	2400GE (YD2400C6M4MFB)	35W	Raven Ridge	3.2GHz	2MB	B0	All
AM4*	Ryzen 5	PRO 1600 (YD160BBM6IAE)	65W	Summit Ridge	3.2GHz	3MB	B1	All
AM4*	Ryzen 5	1600X (YD160XBCM6IAE)	95W	Summit Ridge	3.6GHz	3MB	B1	All
AM4*	Ryzen 5	1600(YD1600BBM6IAF)	65W	Pinnacle Ridge	3.2GHz	3MB	B2	P2.00
AM4*	Ryzen 5	1600 (YD1600BBM6IAE)	65W	Summit Ridge	3.2GHz	3MB	B1	All
AM4*	Ryzen 5	PRO 1500 (YD150BBM4GAE)	65W	Summit Ridge	3.5GHz	2MB	B1	All
AM4*	Ryzen 5	1500X (YD150XBBM4GAE)	65W	Summit Ridge	3.5GHz	2MB	B1	All
AM4*	Ryzen 5	1400 (YD1400BBM4KAE)	65W	Summit Ridge	3.2GHz	2MB	B1	All
AM4*	Ryzen 3	3300X (100-000000159)	65W	Matisse	3.8GHz	2MB	B0	P3.90
AM4	Ryzen 3	PRO 3200G (YD320BC5M4MFH)	65W	Picasso	3.6GHz	2MB	B1	P3.30
AM4	Ryzen 3	PRO 3200GE (YD320BC6M4MFH)	35W	Picasso	3.3GHz	2MB	B1	P3.30
AM4	Ryzen 3	3200G (YD320GC5M4MFH)	65W	Picasso	3.6GHz	2MB	B1	P3.60
AM4	Ryzen 3	3200G (YD3200C5M4MFH)	65W	Picasso	3.6GHz	2MB	B1	P3.30

AM4	Ryzen 3	3200GE (YD3200C6M4MFH)	35W	Picasso	3.3GHz	2MB	B1	P3.30
AM4*	Ryzen 3	3100 (100-000000284)	65W	Matisse	3.6GHz	2MB	B0	P3.90
AM4*	Ryzen 3	2300X (YD230XBBM4KAF)	65W	Pinnacle Ridge	3.5GHz	2MB	B2	All
AM4	Ryzen 3	PRO 2200G (YD220BC5M4MFB)	65W	Raven Ridge	3.5GHz	2MB	B0	All
AM4	Ryzen 3	PRO 2200GE (YD220BC6M4MFB)	35W	Raven Ridge	3.2GHz	2MB	B0	All
AM4	Ryzen 3	2200G (YD2200C5M4MFB)	65W	Raven Ridge	3.5GHz	2MB	B0	All
AM4	Ryzen 3	2200GE (YD2200C6M4MFB)	35W	Raven Ridge	3.2GHz	2MB	B0	All
AM4*	Ryzen 3	PRO 1300 (YD130BBBM4KAE)	65W	Summit Ridge	3.4GHz	2MB	B1	All
AM4*	Ryzen 3	1300X (YD130XBBM4KAE)	65W	Summit Ridge	3.4GHz	2MB	B1	All
AM4*	Ryzen 3	PRO 1200 (YD120BBBM4KAE)	65W	Summit Ridge	3.1GHz	2MB	B1	All
AM4*	Ryzen 3	1200 (YD1200BBM4KAE)	65W	Summit Ridge	3.1GHz	2MB	B1	All
AM4*	Ryzen 3	1200 (YD1200BBM4KAF)	65W	Pinnacle Ridge	3.1GHz	2MB	B2	P2.00
AM4	Athlon	3000G (YD3000C6M2OFH)	35W	Picasso	3.5GHz	1MB	B1	P3.60
AM4	Athlon	Athlon 240GE (YD240GC6M2OFB)	35W	Raven Ridge	3.5GHz	1MB	B0	P1.60
AM4	Athlon	Athlon 220GE (YD220GC6M2OFB)	35W	Raven Ridge	3.4GHz	1MB	B0	P1.60
AM4	Athlon	Athlon PRO 200GE (YD200BC6M2OFB)	35W	Raven Ridge	3.2GHz	1MB	B0	All
AM4	Athlon	Athlon 200GE (YD200GC6M2OFB)	35W	Raven Ridge	3.2GHz	1MB	B0	P1.10
AM4	Athlon	Athlon 200GE(YD20GGC6M2OFB)	35W	Raven Ridge	3.2GHz	1MB	B0	P1.10
AM4	Ryzen 5	3350G(YD3350C5M4MFH)	65W	Picasso	3.6GHz	2MB	B1	P4.90
AM4	Athlon	3000G(YD3000C6M2OFB)	35W	Raven Ridge	3.5GHz	1MB	B0	P4.90